

## JCFLT-907-8-952-8-01-B

1、 Part Number: JCFLT-907-8-952-8-01-B

2、 Name: Filter

3、 Specifications:

Channels	RX	TX
Frequency Range(MHz)	906.6~915	951.6~960
Band Width(MHz)	8.4	8.4
Insertion Loss(dB)	≤1.7 (906.6~907.5MHz)	≤0.6 (951.6~952.5MHz)
	≤1.3 (907.5~915MHz)	≤0.55 (952.5~960MHz)
Ripple in-band(dB)	≤1.0	≤0.2
Stop-band Attenuation(dB)	≥50@<894MHz ≥12@918~921.2MHz ≥30@921.8~944.5MHz ≥35@1000~2850MHz	
PIM(dBc)	≤-140@+43dBm×2	
Group Delay Variation(ns)	≤200	
Absolute Delay(ns)	≤400	
Return Loss(dB)	≥18	
Power Rating(W)	50	
Impedance(Ω)	50	
Connectors	DIN-7/16 (F)	
Temperature(°C)	0~+50	
Size(mm)	251×220×71	
Weight(kg)	3.63	

4、Dimension:

