

JCDUP-8035B-R2A

- 1、 Part Number: JCDUP-8035B-R2A
- 2、 Name: 800-2200 MHz 2-way Combiner
- 3、 Specifications:

Channels	TETRA/CDMA/GSM	DCS/PHS/3G
Frequency Range(MHz)	800~960	1710~2170
Band Width(MHz)	160	460
Insertion Loss (dB)	≤ 0.4	≤ 0.4
Ripple in-band(dB)	≤ 0.3	≤ 0.3
Stop-band Attenuation (dB)	$\geq 90@1710\sim 2170\text{MHz}$	$\geq 90@800\sim 960\text{MHz}$
Isolation(dB)	$\geq 90@1710\sim 2170\text{MHz}$	$\geq 90@800\sim 960\text{MHz}$
Return Loss(dB)	≥ 20	
Impedance(Ω)	50	
PIM3(dBc)	$\leq -140@+43\text{dBm} \times 2$	
Connectors	N-F	
Power Rating(W)	200	
Temperature($^{\circ}\text{C}$)	0~+50	
Size(mm)	27.7×115×38	
Weight(kg)	1.32	

- 4、 Dimension:

